



Alphapoc 602R

Hand programming



1. push **big button** und button ▲ together for about 3 seconds.
2. the display shows: Password: 0000
default password for hand programming is "0000", if not changed by user
3. push button ▼ a couple of times until you see the following:

A: [ON] 1111111
B: [ON] 1222222
4. in this menu you can navigate with ▲ und ▼ .
5. pushing the **big** button you can count down the numbers, pushing the **small** button will count up the numbers.
6. using the **big** and/or **small** button will also change some other preferences, e.g. [On] / [Off] = CapCodes.
7. POCSAG-Polarity ("Polarity") needs to be on status "Normal" !
8. to finish the programming you need to chose at the end of the menu "Program" and push the **small** button.
9. if you like to cancel the changes without programming you can choose at the end of the menu "Exit" and push the **small** button.
10. you need to wait until the display shows „finished“ and the device restarts by itself.

© All rights on pictures and text are reserved!

more information:

Alphapoc – Professional POCSAG DECODING
BS-Electronics GbR * Virchowstr.40 * 66424 Homburg
phone: 049 6841 – 120 / 400 * Alphapoc-Hotline: phone: 0049 6841 – 120 / 412
more information and downloads: www.alphapoc-europe.de Email: support@alphapoc-europe.de

your local dealer:

Alphapoc Support & Services
Hotline: 0049 6841 – 120 / 412
Fax: 0049 6841 – 120 / 409
Email: alphapoc@alphapoc-europe.de